


Ness KPX+ Keypad



Panic Alarm
Press and hold the two emergency keys together for PANIC alarm.
See P126E 1E to enable. See P75E 3E, P191E 3E to enable panic alarm reporting

Fire Alarm
Press and hold the two FIRE (1 & 3) keys together for FIRE alarm.
See P126E 2E to enable keys. See P75E 4E, P191E 4E to enable fire alarm reporting.




Medical Alarm
Press the two Medical (4 & 6) keys together for Medical alarm.
See P126E 3E to enable keys. See P75E 2E, P191E 2E to enable medical alarm reporting.

Adjust Key Beep Volume
Press and hold the **P** key. Release when the desired volume is reached.
The volume level is displayed on the LCD during adjustment.



Adjust Chime Volume
Press and hold the **0** key. Release when the desired volume is reached.
The volume level is displayed on the LCD during adjustment.

Display Test
To display all available LCD icons press and hold the **E** key.
Display Test can be used in any mode.

The **CELL** icon indicates various cellular conditions.

- CELL** with flashing signal strength  indicates the dialler is in use.
-  with flashing **CELL** indicates a cellular dialler fault.
- CELL** with flashing  indicates 'no SIM' Card is fitted.

Adjust LCD Backlight
Press and hold the **9** key to adjust the brightness of the LCD backlight. Release when the desired brightness is reached.

  10 Levels

Note. Beep/Chime Volume and LCD Brightness settings are stored in the keypad. Adjust each keypad individually. Defaults to loudest/highest settings on power down.

Features & Benefits

Ness KPX PLUS new generation LCD keypad now designed with Ness XCEL cellular panels in mind.

Featuring a new high-contrast LCD with adjustable white backlighting, red 'alarm' backlighting and information on-screen for cellular signal strength and network status.

KPX+ is also backward compatible with previous D8x/D16x panels.









- High Contrast LCD icon display
- White and Red LCD backlighting
- Red LCD backlighting for alarm memory
- Adjustable keypad beep volume
- Adjustable LCD brightness
- Supports D8XCEL/D16XCEL cellular panels
- Backward compatible with previous D8x/D16x



COMPATIBLE


Ness KPX+ Keypad

Ness Keypad Compatibility Table

						
Part No	106-100	106-310	106-016 106-015	106-323-WHT 106-323-BLK 106-323-OMT	106-108 106-108-BLK 106-108-OMT	100-001
Description	Navigator Touch Screen Keypad	KPX PLUS LCD Keypad - White	KPX LCD Keypads White/Silver	Saturn PLUS Premium Keypads	Saturn Premium Keypads	Radio Keypad
	✓	✓	✓	✓	✓	✓*
	✓ Navigator Rev3.1 and later	✓	Yes but no cellular status display.	✓	Yes but no cellular status display.	✓*

* With optional Radio Interface

System Configuration



Specifications

Part Number	106-310 KPX PLUS Keypad White
Display Type	High contrast LCD - White backlit / Red backlit (alarm memory)
Compatibility	Ness D8XCEL / D16XCEL Control Panels and earlier
Operating Voltage	12VDC supplied by the control panel
Dimensions	82(W) X 125(H) X 18(D) mm



Innovative Electronic Solutions
www.ness.com.au

